# MODEL JCT-OS RevenueSense<sup>TM</sup>

## Revenue Metering Current Transformer



#### **Application**

RevenueSense™ is a revenue metering current transformer which maintains IEEE 0.15 accuracy class from 1 % of rated current up through rating factor. This is accomplished using the specialized amorphous core material which minimizes electrical core losses. The result is an extremely accurate CT that can maintain high accuracy over a extended range of current. Model JCT-0S is designed for indoor service, and is available in bar-type or window-type designs.

#### **Features**

Voltage Class: 0.6 kV
Insulation Level: 10 kV BIL
Frequency: 50-60 Hz
Application: Indoor

• Window Size: 1.31"

#### Benefits

- Maximize revenue metering accuracy with special high accuracy rating extended beyond IEEE requirements
- Simplify CT selection and billing multipliers, improving productivity and minimizing risk of error
- Reduce inventory and part number requirements, reducing asset and operational costs

| 0.15 Class - High Acci              | uracy |       |    |  |  |  |
|-------------------------------------|-------|-------|----|--|--|--|
| (                                   | ).3%  | 0.15% |    |  |  |  |
| 5%                                  | 100   | % F   | RF |  |  |  |
| 0.15S Class - Special High Accuracy |       |       |    |  |  |  |
| 0.15%                               |       |       |    |  |  |  |
| 5%                                  |       | F     | RF |  |  |  |
| GE Vernova RevenueSense™            |       |       |    |  |  |  |
| 0.15%                               |       |       |    |  |  |  |
| 1%                                  |       | F     | RF |  |  |  |


#### Model JCT-0S


| CURRENT RATIO | ACCIIDACV | RATING | FACTOR |             |            | CATALOG NUMBER | }                       |
|---------------|-----------|--------|--------|-------------|------------|----------------|-------------------------|
| (Amps)        |           | 30°C   | 55°C   | PRIMARY BAR | NO BASE    | LOW BASE       | HIGH BASE               |
| 600:5         | 0.155B0.2 | 2.0    | 1.5    | Yes         | 750X323001 | 750X323002     | 750X323003 <sup>4</sup> |


- $(1) \ \textit{Exceeds IEEE definition for special high accuracy}. \ \textit{Maintains 0.15 Accuracy from 1\% to Rating Factor}.$
- (2) Window-style option available, upon request. Contact GE Vernova for more details.
- (3) Other designs available, upon request. Contact GE Vernova for more details.
- (4) Measurement Canada Approval: AE-2422





#### Model JCT-0S - Dimensions














| REFERENCE DRAWINGS | WEIGHT                |                                  |       |  |  |  |
|--------------------|-----------------------|----------------------------------|-------|--|--|--|
| OUTLINE            | TRANSFORMER, WITH BAR | NSFORMER, WITH BAR LOW BASE, ADD |       |  |  |  |
| 0121C49855         | 7 lbs                 | 0.3 lbs                          | 1 lbs |  |  |  |

#### **Construction and Insulation**

The core and coil are enclosed in a case molded with GE Vernova Valox thermoplastic polyester resin. This tough material has excellent electrical and mechanical properties over a wide temperature range, has low water absorption and is resistant to oil and a variety of chemicals.

#### **Core and Coils**

The core is manufactured with high-efficiency material that reduces energy losses, allowing for higher accuracy over a wider range. The secondary winding is made of heavy enameled copper wire evenly distributed around the core for maximum accuracy and resistance to stray fields from adjacent conductors.

#### **Terminals**

Secondary terminals are tin plated brass, compression type with a 0.275" diameter cross-hole for wiring and a 1/4-28 clamp screw. A shorting device is provided and interlocked to the terminal cover. The terminal cover is made of a clear plastic. Provision is made for sealing the cover.

#### **Polarity**

The H1 polarity mark is molded into the case, above the window at one end. The X1 polarity mark is also molded into the case adjacent to the secondary terminal. Both H1 and X1 are marked with white dots.

#### **Nameplates**

The nameplate is laser engraved aluminum. It is attached to the top of the unit and has provision for attaching the user's identifying tag. The nominal current rating is marked on the side of the unit in large numerals.

#### **Primary Bars**

Formed from solid copper bar, they are tin-plated. They are non-removable and have a potential connector that can be attached above or below the bar at either end.

#### **Baseplate and Mounting**

The transformer can be mounted in any position and may be suspended from the bus-bar or cable. It has provision for attaching two optional bases. Low bases are made from stainless steel. The high base increases the transformer height by 2 inches.

#### Maintenance

These transformers require no maintenance, other than occasional cleaning, if installed where air contamination is severe.

### For more information, visit **gevernova.com/grid-solutions**

Instrument Transformers LLC reserve the right to change specifications of described products at any time without notice and without obligation to notify any person of such changes.

© 2025 GE Vernova and/or its affiliates. All rights reserved. GE and the GE Monogram are trademarks of General Electric Company used under trademark license.

